
KRE-PI600Wx series





Description

Thank you for using the high efficiency and high quality pure sine wave inverter semi-finished energy storage kit of mobile power supply manufactured by KRECO.

The 600W Inverter PCBA kit KRE-PI600Wx uses pure sine wave technology and full power design, which is to facilitate manufacturers, factories in various countries to import mature semi-finished products of KRECO by means of CKD or SKD. It is also an innovative product that customers can assemble energy storage products in their own country after purchasing, and then sell them independently. It perfectly avoids customers' worries about technical shortcomings, high freight, high import tariffs, and dangerous goods battery transportation, and is a truly perfect solution.

The energy storage kit KRE-PI600Wx is an inverter motherboard, does not contain a battery, a charging board, a shell configuration. Please be sure to have a professional team or professional experience in lithium batteries to order assembly storage.

If you are not familiar with this industry, please do not purchase.

Please carefully read and fully understand this kit and know how to use the product to ensure that you can be familiar with the operation and use it correctly.

Be sure to install it safely.

Features

- Pure sine wave technology
- 600W Full power design
- Protections: High temperature protection/ High temperature protection recovery/ Output short circuit protection/ Current limiting protection/ High voltage protection/ Low voltage protection/ Low voltage alarm/ Power temperature control fan/ Constant power overload protection
- W/o batteries, W/o battery charging protection board

of Portable Power Station

KRE-PI600Wx series

KRECO P/N (optional Input DC Voltage)

DC Input Voltage	12VDC	24VDC	48VDC	60VDC	OEM other voltage
KRECO P/N	KRE-PI600W12	KRE-PI600W24	KRE-PI600W48	KRE-PI600W60	Yes

Applications

- Storage power industry
- Consumer electronic devices
- Telecommunication devices
- Office facilities
- Industrial equipment



Specifications and Mechanical Characteristics

Name	SKD Pure Sine Wave Inverter PCBA				
	Rated power	600 W			
	AC output voltage	220~240Vac/ 115Vac available			
	Waveform	Pure sine wave			
	Waveform distortion (THD)	≤5%			
	Frequency	50Hz (50/60Hz adjustable)			
	Frequency range	±0.5			
Output	Continuous output power	600 W (resistive load)			
technical	Peak power	1200 Wer power solutions			
parameters	AC universal socket	2 sockets /2.7A AC/1			
and		\ge 87% (for efficiency test, the sampling point of DC voltage is the voltage at the			
configuration		input end of inverter PCB, the current sampling device (such as current shunt)			
comgaration	Efficiency	shall be used for DC current sampling, and the output power meter of inverter			
		shall be calibrated. When testing the efficiency of the inverter, the load used is a			
		resistive load.			
	USB port	2 ports 5V/3A DC			
	Cigarette lighter socket	1 socket 12VDC 10A			
	LCD screen	1 display show DC voltage, AC voltage, Frequency, Battery Level			
	DC Jack 2.1mm	2 jacks, at 12VDc			

KRECO 景 荣

600W Pure Sine Wave Inverter PCBA kit

of Portable Power Station

KRE-PI600Wx series

	Control switch	3 switches to control AC output, USB, W/ LEDs			
	DC charging interface	XT60E-Female connector, W/o charger			
	Battery voltage	12Vdc	24Vdc		
	Voltage range	Regular 9V-15.5V can be trimmed as required	Regular 19-30.5V can be trimmed as required		
	Off Mode Quiescent Current	≤30uA			
laaut	Fan Operation Mode 1	Temperature-controlled fan: the fan starts when the power reaches approximately 120W; the fan starts when the temperature reaches 40°C to 50°C.			
Input technical	Fan Operation Mode 2	Pure temperature control: the fan starts when the temperature reaches 45°C; the fan stops when the temperature is below 40°C.			
parameters	Cooling fan	2 fans			
	At positive and negative terminals	Tighten and fix the screw			
	Battery type	12V 4-string lithium iron phosphate/ 3-string ternary lithium battery	24V 8-string lithium iron phosphate/ 7-string ternary lithium battery		
	Battery low voltage alarm	10±0.5V DC	20±0.5V DC		
	Battery low voltage protection	9V off inverter output	19V off inverter output		
	Battery high voltage protection	16V off inverter output	31V off inverter output		
	High temperature protection	80°C	B		
	High temperature protection recovery	Restart below 60°C			
	Output short circuit protection	Automatic recovery of light short circuit, long short circuit exceeding 3 seconds to shut down the front/input stage, restart the machine.			
Output	Current limiting protection	Yes			
protections	High voltage protection	Yes			
	Low voltage protection	Yes			
	Low voltage alarm	Yes			
	Power temperature control fan	Yes			
	Constant power overload protection	1.7 times of the maximum output of constant power, automatic shutdown			
	Operating temperature	-20°C ~ 50°C			
Environment	Storage temperature and humidity	-40°C ~ 60°C,10 ~ 95%RH			
	Body size	27 x 14.7 x 16.5 cm (LxWXH)			
	Size of battery compartment	19.5 x 14 x 10.3 cm (LxWXH)			
Volume and	Package size of the complete set	32.5 x 20.5 x 21.5 cm (LxWXH)			
package	Bare metal weight	Net weight: 3.05 kgs			
	Weight of the complete set	Gross weight: 3.4 kgs			

KRECO[®] 景 荣

KRE-PI600Wx series

■ Outlook and Installation Example Unit: cm

Recommend lithium iron phosphate/ ternary lithium battery

纯正弦波足功率600W



Note

- (1) AC universal socket type is for worldwide power plugs, more plugs type could be re-designed, or added to production order.
- (2) X= Input DC voltage, it is optional, according to design.
- (3) 600W for Output power, what you are going to order, please must specify to sales.
- (4) Safety model number may differs from the order number, KRECO P/N number, and shape number as per respective OEM/ODM factories.
- (5) Please be sure to have a professional team or professional experience in lithium batteries to order assembly storage.
- (6) Please carefully read and fully understand this kit and know how to use the product to ensure that you can be familiar with the operation and use it correctly.
- (7) Be sure to install it safely.

Disclaimer:

Kreco is not responsible for any error, and reserves the right to make changes without notice.

Please visit our website at www.krecocharger.com or https://www.ipskre.com for the most up-to-date specifications and contact information.